

TITLE: Missing or Outdated Parallel Port Device Driver Error

Category: Software – OMEGA - Errors

Gerber FastFact #: 3551

Supplied by: Gerber Service

Last Modified: 7/23/04

Summary: This document explains how to fix the Missing or Outdated Parallel Port Device

Driver Error

Underlined text indicates change from the previous document.

**SOLUTION** to receiving 'Missing or Outdated Parallel Port Device Driver' error message when outputting to an EDGE/EDGE2

- 1. Open GQ Mgr.
- 2. Go to HELP then ABOUT.
- 3. The version will probably read:?,?,?,? If it reads 4,6,0,0 the following fix might not help you.
- Close GQ Mgr.
- 5. Run the Warp9fix program found on the Omega CD under MISC.
- Copy the Parcheck.exe file from the Omega MISC. Folder to the following directory on the hard drive: WINDOWS\SYSTEM32\DRIVERS

(May be WINNT\SYSTEM32\DRIVERS in Windows 2000 and windows XP)

- 7. Run Parcheck.exe from the above directory.
- 8. Go to Device Manager.
- 9. Click on View.
- 10. Click Show Hidden Devices.
- 11. Double click on Non Plug & Play Drivers.
- 12. Double click on Par1284.
- 13. Click on the Driver tab.
- 14. Check that the status is STARTED. If it is stopped click on START
- 15. Choose AUTOMATIC from the Startup Type
- 16. Click OK.
- 17. Exit Device Manager.
- 18. Re-boot the computer.
- 19. Once restarted, open GQ Mgr.
- 20. Go to HELP then ABOUT.
- 21. The version should now read: 4,6,0,0
- 22. Open Composer and output a job to your Edge/Edge2. The output should be successful.